

toy center

Un diffusore per riprodurre la voce con ariosità e precisione. Grazie al suo equilibrio timbrico, Toy center è il piccolo canale centrale perfettamente integrato con la linea Toy, che consente a quest'ultima di inserirsi, con estrema semplicità e fruibilità, in tutte le applicazioni non strettamente stereofoniche - quali le varie configurazioni multicanale e multimediali - che richiedono la qualità dei diffusori Sonus faber per garantire una riproduzione appassionata e coinvolgente.

The Toy Center is engineered to reproduce the human voice with dynamism and precision. With its unique timbral balance and compact dimensions, the Toy Center integrates perfectly with other Toy models. It makes a simple but highly effective addition to Toy speakers used in multichannel and multimedia configurations - all of which benefit from the passionate and enveloping experience delivered with full intensity by the legendary quality of Sonus Faber loudspeakers.

FINISH:
Barred black leather.

DIMENSIONS:
165 x 540 x 225 mm (HxWxD).

WEIGHT:
7.3 Kg – net weight / 9.5 Kg – shipping weight.

SYSTEM:
2 way vented box loudspeaker.

CABINET:
Construction with decoupled side panels for resonances and standing waves control.

TWEETER:
25 mm ultra dynamic ring radiator-driver, neodymium magnet system.

MID-WOOFERS:
110 mm coated cellulose cone drivers.

CROSS-OVER:
Non-resonant third order design, optimized phase characteristics for optimal space/time performance, cross-over point 2.000 Hz.

FREQUENCY RESPONSE:
55 Hz – 25.000 Hz, tuning ports included.

SENSITIVITY:
89 dB SPL (2.83 V/1m).

NOMINAL IMPEDANCE:
8 ohm.

POWER HANDLING:
20W – 100W, without clipping.

